


## Mobile View Function User Manual(BlackBerry)



### Recommended Mobile Phone List

BlackBerry 9700  
BlackBerry 8900  
BlackBerry 9500  
BlackBerry 9000

BlackBerry OS 5.0



**Recommended use 3G or WIFI network, to obtain the better preview effect.**

**DVR configuration:**

**Note:**

1. Please make sure that your DVR has Internet IP, and can be accessed via internet.
2. Please make sure that your DVR supports mobile view function.(It depends on the DVR Firmware version.)

**Operation Steps:****7004/ 7008/ 7016:**


Menu->Network->Platform Server Setting->Load to enter the mobile port setting interface



You need to set the listen port (command port) and choose the channels you want to view. (default listen port is 15966 ,range is 1-65535, you can change it by yourself ,all channels default disable),and you need do the listen port router mapping in your router. Please keep other box in this interface as the default status. Please click connect to save the setting.




Through the Main menu-> record pare to enter the network stream setting interface. User need to reduce the network stream. We suggest that choose the bitrate to 100K of each channel ,and the frame rate is 8 fps of each channel. Remember save the setting.




## 7000M/7000T2/7024/ 8000/ 8200:

Menu->Network->Server->Huake->Load to enter the mobile port setting interface




You need to set the listen port (command port) and choose the channels you want to view. (default listen port is 15966 ,range is 1-65535, you can change it by yourself ,all channels default disable),and you need do the listen port router mapping in your router. Please keep other box in this interface as the default status. Please click connect to save the setting.



Through the Main menu->record setting-> record pare to enter the network stream setting

interface. User need to reduce the network stream. We suggest that choose the bitrate to 100K of each channel ,and the frame rate is 8 fps of each channel. Remember save the setting.




## Router Configuration:

If the DVR connected to WAN through router, you need to do the command port (default 8101),http port (default 81),listen port(default 15966) router mapping .Take the TP-Link router as an example.

1. Do the port mapping in the router. Forward the listen port which your DVR set, default is **15966**.



1. Do not forget forward other 2 ports which used on DVR internet setting.




Notes: if the DVR was connected to WAN through directly DDNS or PPPOE, you just need to do the listen port (default 15966) router mapping.

## Mobile Phone Configuration


Take the BlackBerry 9700 as an example.

### Installation steps:

1. You should first install the BlackBerry Desktop Manager on your mobile.



2. Then connecting BlackBerry phone to PC .
3. Enter the application loader and choose add software.



4. Choose to install the player.alx as your save path.
5. After installation successfully, you will find the player in mobile Download file.



## **Login and preview:**

1. Click the HBplayer to enter the main interface as follows:



2.You should input the corresponding login information to the login interface as below. Such as DVR username, password, DVR address (IP or Domain name).Server port means the mobile command port (default 15966).



3.After that, click Login to view the DVR Live image on mobile phone.



Function button:

- 1.play / pause
- 2.Full screen
- 3.Snapshot
- 4.Setup
- 5.Mobile client Imprint
- 6.Channels switch(1-8, 9-16 and PTZ control)
- 7.Channels NO. and PTZ control button



- 1.Direction control(1-4)
- 2.Focus(5-6)
- 3.Zoom(7-8)
- 4.Iris(9-10)